

Categories		2-way Loudspeaker					
Model Name		VKE2015	VKE2015	VKE2012	VKE2012	VKE2010	VKE2010
DME library file name		VKE2015.cel	VKE2015_vocal.cel	VKE2012.cel	VKE2012_vocal.cel	VKE2010.cel	VKE2010_vocal.cel
Drive Mode		Passive	Passive	Passive	Passive	Passive	Passive
Output Name		Full-range	Full-range	Full-range	Full-range	Full-range	Full-range
Gain	(dB)	0.0	0.0	0.0	0.0	0.0	0.0
Delay	(ms)	none	none	none	none	none	none
Polarity		Normal	Normal	Normal	Normal	Normal	Normal
HPF	Freq (Hz)	40.0	40.0	40.0	40.0	40.0	40.0
	Slope (dB)	12	12	12	12	12	12
	Type	Butterworth	Butterworth	Butterworth	Butterworth	Butterworth	Butterworth
LPF	Freq (Hz)						
	Slope (dB)						
	Type						
PEQ1	Freq (Hz)	45.0	45.0	50.0	50.0	54.6	54.6
	Level (dB)	6.0	6.0	4.0	5.0	4.5	6.0
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	1.5	1.5	1.5	1.5	1.6	1.6
	Bandwidth	0.945	0.945	0.945	0.945	0.888	0.888
PEQ2	Freq (Hz)	345	180	1000	200	280	280
	Level (dB)	-3.0	2.5	-2.0	1.5	-3.5	-3.0
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	3.0	2.2	3.3	1.8	2.0	2.0
	Bandwidth	0.479	0.650	0.436	0.792	0.714	0.714
PEQ3	Freq (Hz)	1,600	345	2,360	1,500	1,220	1,220
	Level (dB)	-2.3	-3.0	-9.0	2.5	0.5	4.5
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	0.8	3.0	2.5	2.0	1.0	1.0
	Bandwidth	1.703	0.479	0.573	0.714	1.388	1.388
PEQ4	Freq (Hz)	2,180	1,000	2,590	2,500	2,590	2,590
	Level (dB)	-4.8	-1.0	1.0	-6.0	-5.5	-5.5
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	2.4	0.8	1.25	3.0	3.3	3.3
	Bandwidth	0.697	1.703	1.125	0.479	0.436	0.436
PEQ5	Freq (Hz)	3,350	2,240	5,160	5,160	5,460	5,460
	Level (dB)	-4.0	-2.0	-3.5	-3.5	-5.0	-5.0
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	2.5	1.4	5.0	5.0	6.3	6.3
	Bandwidth	0.573	1.010	0.288	0.288	0.229	0.229
PEQ6	Freq (Hz)	9,000	10,000	8,500	10,900	10,000	10,000
	Level (dB)	-1.8	2.0	-1.8	2.1	2.00	3.0
	Type	Bell	Bell	Bell	Bell	Bell	Bell
	Q	3.5	3.5	3.8	1.05	2.0	2.0
	Bandwidth	0.411	0.411	0.379	1.327	0.714	0.714
Limiter	Threshold	700W	700W	700W	700W	600W	600W
	Attack	MID	MID	MID	MID	MID	MID
	Release	MID	MID	MID	MID	MID	MID